

# LOK-IT HTI 1500W/60/P50 M3W 1/CS 1/SKU



#### Product features and benefits

- Compact design and short arc gap allows for smaller and brighter fixures
- Fast lamp replacement with one-touch rotate and lock base and socket design
- Robust design with eXtreme Seal (XS) technology, allowing up to 450°C at the pinch seal
- Consistent lumen output over the life of the lamp
- Improved ceramic base allows high voltage up to 35kV
- Higher luminous efficacy than conventional HID lamps provides higher fixture efficiency

### Areas of application

- Concert lighting
- Club & Disco
- Stage and theatre
- Studio, TV and film
- Architecture & Architainment

# Product datasheet

### Technical data

# **General product information**

Product Number	54396		
Product Name	LOK-IT HTI 1500W/60/P50 M3W 1/CS 1/SKU		
Family Brand Name	Lok-it!		
Application	Entertainment and Effect Lighting		
Product Remark	<ul> <li>Optimized lamp eXtreme Seal (XS) technology to withstand interior base temperatures of up to 450 degrees celsius.</li> </ul>		

### **Electrical data**

Nominal Wattage	1500 W
Nominal Voltage	100 V
Current (A)	15

# Light technical data

Luminous Flux	130000 lm	
Light Center Length - LCL (mm)	65 mm	
Color Temperature	6000 K	
Average Rated Life	750 h	

# Physical attributes

Base	PGJX50
Bulb Shape	Т
Maximum Overall Length (mm)	128 mm
Length I (mm)	128 mm
Diameter d (mm)	29
Distance a (mm)	65 mm
Electrode Gap - cold (mm)	7 mm

# Additional product data

Lampholder	PGJX50
Operating Position	Any
Maximum Base Temperature (°C)	450 C
Cooling	Required
Forced Cooling	Required
Hot Restart	No

### Product datasheet

#### **Packaging Information**

Product number	EAN/UPC	Packaging	Quantity	Outside dimensions l x w x h	Gross weight
54396	4008321818997	Shipping box (Case)	1	4.5 in x 3.2 in x 12 in	0.6 lb

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

#### Disclaimer

OSRAM does not accept liability for errors, changes and omissions.